



Data subject to change without notice. Always confirm the data is correct from the seller.

## KU 3160

### KU Rotary switches and change-over switches 100-160A

- Modular design
- DIN-rail mounting
- 3-pole and 4-pole KU-switches as standard
- Change-over switches: CO included in type name
- 6-pole and 8-pole versions consist of two 3-pole or 4-pole KU-switches connected by a parallel kit
- Switch technology by means of silver contacts ensures safe and durable operation
- Compatible with handles LK10 and LK11 (3 and 4 poles) and LK12 (6 and 8 poles) and LK12CO102 (change-over switch)
- Shafts L=100/200/300 AD11 and L=100/200/300 AD11/VT (3 and 4 poles), L=100/200/300 AD12/VT (6 and 8 poles and change-over switch)
- **Note!** Al-cables cannot be connected directly to switch terminals. For Al-cable connection please use a bi-metal cable connector, **available here.**

Technical Data

Accessories

Handle & Shaft



## Product details

<b>SKU</b>	KU 3160
<b>AC-22 400/415 V (A)</b>	160 A
<b>AC-22 690 V (A)</b>	160 A
<b>AC-23 400/415 V (A/kW)</b>	160 A / 90 kW
<b>AC-23 690 V (A/kW)</b>	100 A / 90 kW
<b>Cable Area to Switch Terminal (only Cu) (mm<sup>2</sup>) / Bolt size</b>	6-70
<b>E-Number</b>	3600787
<b>EAN</b>	6419410203507
<b>Number of Poles</b>	3
<b>Operation</b>	Rotary
<b>Switch type</b>	Load Break Switch
<b>Weight (kg)</b>	0.45

## Dimensional drawing

